

VMX-B^{25 to 1080A}

BASIC CONFIGURED SOFT STARTER



NEMA 4/12 Enclosure

Start Rated Bypass Contactor

Available with Circuit breaker, Fused Disconnect or MLO

VMX Digital Starter

120V Control Voltage (CPT included)

Illuminated E-STOP Pushbutton

Start/Stop Pushbutton and Motor Run Light Assembly

Local/Off/Remote Selector

Fault Light / Reset Pushbutton

Terminal Strip for Customer Interface

Surge Device Installed

VMX-B Command Center

- Emergency Stop Pushbutton
- Start/Stop Pushbutton
- Local / Off / Remote Switch
- Power On Light
- Motor Run Light
- Start Fault / Reset Light
- Check E-Stop Light

Flexibility of Control

Multiple ramp profiles, Pump-Flex™ Decel and advanced motor protection make the VMX Series soft starter adaptable to a wide variety of AC motor applications... no need for add-on modules or costly auxiliary devices.

Compact packaging has become critical in more and more electrical installations. The VMX Series meets this need without compromising features and ratings. By using a highly engineered packaging design and the latest generation microprocessor, all the control and protection features you need are in the VMX Series. Narrow and shallow dimensions are perfect for integrating the VMX Series into motor control centers (MCCs), pump control panels, and retrofit starter enclosures.

Integral Start Rated Bypass Contactors are standard on all sizes and provide maximum efficiency of panel space while maintaining the Motortronics reputation for being able to soft start most any load. The VMX Series is the only fully integrated, compact, world-class design offering uncompromised power and control

Model Number	Max Amps	Nominal Motor HP Rating				Fused Switch/ Circuit Breaker	Frame Size
		208V	240V	480V	575V		
VMX-B-21-YY-X	25	7.5	7.5	15	20	40A FS	1
VMX-B-27-YY-X	34	10	10	25	30	50A FS	1
VMX-B-40-YY-X	42	10	15	30	30	60A FS	1
VMX-B-45-YY-X	54	15	20	40	50	100A CB	1
VMX-B-55-YY-X	68	20	25	50	60	100A CB	1
VMX-B-68-YY-X	80	25	30	60	75	100A CB	1
VMX-B-96-YY-X	96	30	30	75	75	150A CB	1
VMX-B-125-YY-X	130	40	50	100	75	250A CB	1
VMX-B-156-YY-X	180	60	60	150	150	250A CB	2
VMX-B-220-YY-X	192	60	75	150	150	400A CB	2
VMX-B-230-YY-X	250	75	100	200	250	400A CB	2
VMX-B-248-YY-X	312	100	125	250	300	400A CB	2
VMX-B-400-YY-X	361	125	150	300	300	600A CB	2
VMX-B-480-YY-X	480	150	200	400	500	800A CB	2
VMX-B-600-YY-X	590	200	200	500	600	800A CB	2
VMX-B-690-YY-X	722	250	300	500	600	1200A CB	2 ½
VMX-B-800-YY-X	750	-	300	600	600	1200A CB	2 ½
VMX-B-960-YY-X	960	300	400	800	900	1200A CB	3
VMX-B-1080-YY-X	1080	350	450	900	1,000	1600A CB	3



VMX-B Series

YY = Line Input Device

MLO = Main Lug only (no disconnect or short circuit protection)
 FS = Fused Disconnect (with Class J fuses, available on models 21, 27 and 40)
 CB = Line Circuit Breaker (available on model 45 and above)

X = Line & Control Voltage (50/60Hz)

1 = 208V, 120V Ctrl. 4 = 480V, 120V Ctrl.
 2 = 240V, 120V Ctrl. 5 = 575V, 120V Ctrl.

NOTES:

- 1 – Size the Soft Starter based on the actual motor nameplate FLA.
- 2 – The units listed are rated for 500% overload capacity for 60 sec., 1.15 S.F.
- 3 – Enclosed units include line + load lugs.
- 4 – The above data is based on the NEC Table 430-150, full load current for 3 phase motors.

VMX-B DIMENSIONS

Frame Size	NEMA 4/12*	Dimensions H x W x D
1	Wall Mount	37" x 15" x 12" (934 x 381 x 305 mm)
2	Wall Mount	48" x 33" x 16" (1219 x 838 x 406 mm)
2 ½	Floor Standing	87" x 32" x 24" (2210 x 813 x 610 mm)
3	Floor Standing	90" x 39.5" x 24" (2286 x 1003 x 610 mm)

- 5 – Model 600 @ 480V / 575VAC is 1.0 S.F.
- 6 – 65KA Rated units available – Consult Factory for pricing.
- 7 – A Space Heater is recommended for units installed outdoors.



USA HEADQUARTERS

Motortronics / Phasetronics
 1600 Sunshine Drive
 Clearwater, Florida 33765
 USA
 Tel: + 727-573-1819 / 888-767-7792
 Fax: + 727-573-1803 / 800-548-4104
 E-mail: sales@motortronics.com
www.motortronics.com

UNITED KINGDOM

Motortronics UK
 Bristow House,
 Gillard Way, Ivybridge,
 Devon, PL21 9GG,
 United Kingdom
 Tel: +44 (0)1752-894554
www.motortronics-uk.co.uk

SOUTH KOREA

Motortronics Int'l Korea Co Ltd
 #1607, 128 Gasan digital 1-ro,
 Gasan digital 1-ro,
 Geumcheon-gu,
 Seoul 08507, Republic of Korea
 Tel: 82-2-867-5808
 Fax: 82-2-867-6004
www.motortronics-korea.com

CHINA

M & P Machinery & Electronics Control
Part of the Motortronics Group
 32 Jiaxin Road,
 Jimo,
 Qingdao, China 266229
 Tel: 86-532-81725028
 Fax: 86-532-81725038
www.mp-cn.com

UNITED ARAB EMIRATES

Motortronics MEA, LLC
 Sharjah Media City,
 Sharjah,
 United Arab Emirates
 Tel: +1 971-50 763 4920
www.motortronics.com

PN: MT-VMXB-080620